

<IGBT Modules>

CM450DX-24T/CM450DXP-24T

HIGH POWER SWITCHING USE INSULATED TYPE

		Collector current Ic 4 5 0 A
	the second	Collector-emitter voltage V_{CES} 1 2 0 0 V
		Maximum junction temperature T _{vjmax} 1 7 5 °C
DX		●Flat base type
		 Copper base plate (Ni-plating)
		RoHS Directive compliant
		 Tin plating pin terminals
		Collector current Ic 4 5 0 A
		Collector-emitter voltage V_{CES} 1 2 0 0 V
		Maximum junction temperature T_{vjmax} 1 7 5 °C
DXP	A A A A A A A A A A A A A A A A A A A	●Flat base type
		 Copper base plate (Ni-plating)
	and the second	 RoHS Directive compliant
		 Tin plating pressfit terminals
	dual switch (half-bridge)	●UL Recognized under UL1557, File No. E323585

APPLICATION


AC Motor Control, Motion/Servo Control, Power supply, etc.

OPTION (Below options are available.)


•PC-TIM (Phase Change Thermal Interface Material) pre-apply (Note10)


•V_{CEsat} selection for parallel connection

INTERNAL CONNECTION



OUTLINE DRAWING






Tolerance otherwise specified

Division of	Tolerance	
0.5	to 3	±0.2
over 3	to 6	±0.3
over 6	to 30	±0.5
over 30	to 120	±0.8
over 120	to 400	±1.2





Toterance otherwise specified							
Divisio	n of l	Tolerance					
	0.5	to	3	±0.2			
over	3	to	6	±0.3			
over	6	to	30	±0.5			
over	30	to	120	±0.8			
over 120		to 400		±1.2			

MAXIMUM RATINGS (Tvj=25 °C, unless otherwise specified) INVERTER PART IGBT/FWD

Symbol	Item	Conditions	Rating	Unit	
V _{CES}	Collector-emitter voltage	G-E short-circuited	1200	V	
V_{GES}	Gate-emitter voltage	C-E short-circuited	± 20	V	
lc	Collector current	DC, T _C =118 °C (Note2, 4)	450	A	
I _{CRM}		Pulse, Repetitive (Note3)	900		
Ptot	Total power dissipation	T _C =25 °C (Note2, 4)	2500	W	
IE (Note1)	Emitter eurrent	DC (Note2)	450	^	
IERM (Note1)	Emitter current	Pulse, Repetitive (Note3)	900	A	

MODULE

Symbol	Item Conditions		Rating	Unit
Visol	Isolation voltage	Terminals to base plate, RMS, f=60 Hz, AC 1 min	2500	V
T _{vjmax}	Maximum junction temperature	Instantaneous event (overload) (Note10)	175	°C
T _{Cmax}	Maximum case temperature	(Note4, 10)	125	
Tvjop	Operating junction temperature	Continuous operation (under switching) (Note10)	-40 ~ +150	°C
Tstg	Storage temperature	-	-40 ~ +125	C

ELECTRICAL CHARACTERISTICS (T_{vj} =25 °C, unless otherwise specified) INVERTER PART IGBT/FWD

Symbol	ol Item Conditions				Limits		Unit
Symbol	Item	Conditions		Min.	Тур.	Max.	
CES	Collector-emitter cut-off current	V _{CE} =V _{CES} , G-E short-circuited		-	-	1.0	mA
I _{GES}	Gate-emitter leakage current	V _{GE} =V _{GES} , C-E short-circuited		-	-	0.5	μA
$V_{GE(th)}$	Gate-emitter threshold voltage	I _C =45 mA, V _{CE} =10 V		5.4	6.0	6.6	V
		I _C =450 A, V _{GE} =15 V,	T _{vj} =25 °C	-	1.65	2.05	
V _{CEsat}		Refer to the figure of test circuit	T _{vj} =125 °C	-	1.85	-	V
(Terminal)		(Note5)	T _{vj} =150 °C	-	1.90	-	
	Collector-emitter saturation voltage	I _C =450 A,	T _{vi} =25 °C	-	1.50	1.75	
V _{CEsat}		V _{GE} =15 V,	T _{vj} =125 °C	-	1.70	-	V
(Chip)		(Note5)	T _{vj} =150 °C	-	1.75	-	
Cies	Input capacitance			-	-	109.1	nF
Coes	Output capacitance	V _{CE} =10 V, G-E short-circuited		-	-	3.1	
Cres	Reverse transfer capacitance	-		-	-	1.4	
Q _G	Gate charge	V _{CC} =600 V, I _C =450 A, V _{GE} =15 V		-	3.4	-	μC
t _{d(on)}	Turn-on delay time	V _{cc} =600 V, I _c =450 A, V _{GE} =±15 V,		-	-	600	- ns
tr	Rise time			-	-	200	
t _{d(off)}	Turn-off delay time			-	-	800	
t _f	Fall time	$-$ R _G =1.3 Ω , Inductive load		-	-	400	
		I _E =450 A, G-E short-circuited,	T _{vj} =25 °C	-	1.70	2.25	
V _{EC} ^(Note1)		Refer to the figure of test circuit	T _{vj} =125 °C	-	1.85	-	V
(Terminal)		(Note5)	T _{vj} =150 °C	-	1.90	-	
()]=+=4)	Emitter-collector voltage	I _E =450 A,	T _{vj} =25 °C	-	1.50	1.85	
V _{EC} (Note1)		G-E short-circuited,	T _{vj} =125 °C	-	1.50	-	V
(Chip)		(Note5)	T _{vj} =150 °C	-	1.50	-	
t _{rr} ^(Note1)	Reverse recovery time	V _{CC} =600 V, I _E =450 A, V _{GE} =±15 V,		-	-	400	ns
Q _{rr} ^(Note1)	Reverse recovery charge	R_{G} =1.3 Ω , Inductive load		-	35.1	-	μC
Eon	Turn-on switching energy per pulse	V _{CC} =600 V, I _C =I _E =450 A,		-	43.1	-	
E _{off}	Turn-off switching energy per pulse	V _{GE} =±15 V, R _G =1.3 Ω, T _{vj} =150 °C,		-	45	-	mJ
Err (Note1)	Reverse recovery energy per pulse	Inductive load		-	32.4	-	mJ
R _{CC'+EE'}	Internal lead resistance	Main terminals-chip, per switch, Tc=25 °	°C (Note4)	-	0.75	-	mΩ
r _g	Internal gate resistance	Per switch		-	0.67	-	Ω

ELECTRICAL CHARACTERISTICS (cont.; T_{vj} =25 °C, unless otherwise specified) NTC THERMISTOR PART

Symbol	Itom	Conditions		Unit		
	Item Conditions		Min.	Тур.	Max.	Unit
R ₂₅	Zero-power resistance	T _C =25 °C (Note4)	4.85	5.00	5.15	kΩ
ΔR/R	Deviation of resistance	R ₁₀₀ =493 Ω, T _C =100 °C (Note4)	-7.3	-	+7.8	%
B _(25/50)	B-constant	Approximate by equation (Note6)	-	3375	-	К
P ₂₅	Power dissipation	T _C =25 °C (Note4)	-	-	10	mW

THERMAL RESISTANCE CHARACTERISTICS

Symbol	Itom	Conditions		Limits			Unit
Symbol	Item			Min.	Тур.	Max.	Unit
R _{th(j-c)Q}	Thermal resistance	Junction to case, per Inverter IGBT (Note4)		-	-	60	K/kW
R _{th(j-c)D}	Thermai resistance	Junction to case, per Inverter FWD (Note4)		-	-	87	r/kvv
Б	Contact thermal resistance	Case to heat sink, Thermal	rease applied (Note4, 7,10)	-	11.5	-	K/kW
$R_{th(c-s)}$	Contact thermal resistance	per 1 module, PC-TIM a	oplied (Note4, 8,10)	-	3.1	-	r\/KVV

MECHANICAL CHARACTERISTICS

Symbol	Item	Conditions			Unit		
	Item	Cor	Conditions			Max.	Unit
Mt	Mounting torque	Main terminals	M 6 screw	3.5	4.0	4.5	N∙m
Ms	Mounting torque	Mounting to heat sink	M 5 screw	2.5	3.0	3.5	N∙m
		Solder nin tune (DV)	Terminal to terminal	17	-	-	
-l	Creepage distance	Solder pin type (DX)	Terminal to base plate	16.4	-	-	mm
ds		Pressfit pin type (DXP)	Terminal to terminal	17	-	-	mm
			Terminal to base plate	16.8	-	-	
		Solder pin type (DX)	Terminal to terminal	10	-	-	mm
-			Terminal to base plate	16.2	-	-	
da	Clearance		Terminal to terminal	10	-	-	
		Presstit pin type (DXP)	Pressfit pin type (DXP) Terminal to base plate		-	-	mm
ec	Flatness of base plate	On the centerline X, Y	On the centerline X, Y (Note9)		-	+200	μm
m	mass	-		-	300	-	g

*. This product is compliant with the Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment (RoHS) directive 2011/65/EU and (EU) 2015/863.

Note1. Represent ratings and characteristics of the anti-parallel, emitter-collector free-wheeling diode (FWD).

- 2. Junction temperature (T $_{\nu j}$) should not increase beyond T $_{\nu j\,m\,ax}$ rating.
- 3. Pulse width and repetition rate should be such that the device junction temperature (T_{vj}) dose not exceed T_{vjmax} rating.
- 4. Case temperature (T_C) and heat sink temperature (T_S) are defined on the each surface (mounting side) of base plate and heat sink just under the chips. Refer to the figure of chip location.


5. Pulse width and repetition rate should be such as to cause negligible temperature rise. Refer to the figure of test circuit.

6.
$$B_{(25/50)} = \ln(\frac{R_{25}}{R_{50}})/(\frac{1}{T_{25}} - \frac{1}{T_{50}})$$

 $R_{25}\!\!:$ resistance at absolute temperature T_{25} [K]; $T_{25}\!\!=\!\!25$ [°C]+273.15=298.15 [K]

- R_{50} : resistance at absolute temperature T_{50} [K]; $T_{50}\text{=}50$ [°C]+273.15=323.15 [K]
- 7. Typical value is measured by using thermally conductive grease of λ =0.9 W/(m·K)/D_(C-S)=50 µm.
- 8. Typical value is measured by using PC-TIM of λ =3.4 W/(m·K)/D_(C-S)=50 µm.

9. The base plate (mounting side) flatness measurement points (X, Y) are shown in the following figure.




10. Long term performance related to thermal conductive grease and PC-TIM (including but not limited to aspects such as the increase of thermal resistance due to pumping out, etc.) should be verified under your specific application conditions. Each temperature condition (T_{vj max}, T_{vj op}, T_{C max}) must be maintained below the maximum rated temperature throughout consideration of the temperature rise even for long term usage.

Note11. Use the following screws when mounting the printed circuit board (PCB) on the standoffs. PCB thickness : t1.6


	Туре	Manufacturer	Size	Tightening torque (N⋅m)	Recommended tightening method
(1)	PT®	EJOT	K25×8	0.55 ± 0.055	
(2)	PT®		K25×10	0.75 ± 0.075 N∙m	by handwork (equivalent to 30 rpm
(3)	DELTA PT®		25×8	0.55 ± 0.055 N∙m	by mechanical screw driver)
(4)	DELTA PT®		25×10	0.75 ± 0.075 N∙m	~ 600 rpm (by mechanical screw driver)
(5)	B1	-	φ2.6×10	0.75 ± 0.075 N ⋅ m	
	tapping screw		φ2.6×12	0.75 ± 0.075 N•III	

RECOMMENDED OPERATING CONDITIONS

Symbol	Item	Conditions	Limits			Unit
Symbol	item	Conditions	Min.	Тур.	Max.	Unit
V _{cc}	(DC) Supply voltage	Applied across C1-E2 terminals	-	600	850	V
V_{GEon}	Gate (-emitter drive) voltage	Applied across G1-E1s/G2-E2s terminals	13.5	15.0	16.5	V
R _G	External gate resistance	Per switch	1.3	-	10	Ω





Tr1/Tr2: IGBT, Di1/Di2: FWD, Th: NTC thermistor




Option: PC-TIM applied baseplate outline


TEST CIRCUIT AND WAVEFORMS






trr, Qrr characteristics test waveform






IGBT Turn-off switching energy



FWD Reverse recovery energy

Switching energy and Reverse recovery energy test waveforms (Integral time instruction drawing)


TEST CIRCUIT




PERFORMANCE CURVES


INVERTER PART






COLLECTOR-EMITTER VOLTAGE CHARACTERISTICS (TYPICAL)






FREE WHEELING DIODE FORWARD CHARACTERISTICS (TYPICAL)




PERFORMANCE CURVES


INVERTER PART

HALF-BRIDGE SWITCHING CHARACTERISTICS (TYPICAL)




HALF-BRIDGE SWITCHING CHARACTERISTICS (TYPICAL)





HALF-BRIDGE SWITCHING CHARACTERISTICS (TYPICAL)




HALF-BRIDGE SWITCHING CHARACTERISTICS (TYPICAL)


PERFORMANCE CURVES

INVERTER PART


CAPACITANCE CHARACTERISTICS (TYPICAL)



FREE WHEELING DIODE REVERSE RECOVERY CHARACTERISTICS (TYPICAL)



TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS (MAXIMUM)




Publication Date : December 2020

GATE CHARGE Q_G (nC)


PERFORMANCE CURVES

INVERTER PART

TURN-OFF SWITCHING SAFE OPERATING AREA (REVERSE BIAS SAFE OPERATING AREA) (MAXIMUM)




NTC thermistor part





SHORT-CIRCUIT SAFE OPERATING AREA (MAXIMUM)



Important Notice

The information contained in this datasheet shall in no event be regarded as a guarantee of conditions or characteristics. This product has to be used within its specified maximum ratings, and is subject to customer's compliance with any applicable legal requirement, norms and standards.

Except as otherwise explicitly approved by Mitsubishi Electric Corporation in a written document signed by authorized representatives of Mitsubishi Electric Corporation, our products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury.

In usage of power semiconductor, there is always the possibility that trouble may occur with them by the reliability lifetime such as Power Cycle, Thermal Cycle or others, or when used under special circumstances (e.g. condensation, high humidity, dusty, salty, highlands, environment with lots of organic matter / corrosive gas / explosive gas, or situations which terminals of semiconductor products receive strong mechanical stress). Therefore, please pay sufficient attention to such circumstances. Further, depending on the technical requirements, our semiconductor products may contain environmental regulation substances, etc. If there is necessity of detailed confirmation, please contact our nearest sales branch or distributor.

The contents or data contained in this datasheet are exclusively intended for technically trained staff. Customer's technical departments should take responsibility to evaluate the suitability of Mitsubishi Electric Corporation product for the intended application and the completeness of the product data with respect to such application. In the customer's research and development, please evaluate it not only with a single semiconductor product but also in the entire system, and judge whether it's applicable. As required, pay close attention to the safety design by installing appropriate fuse or circuit breaker between a power supply and semiconductor products to prevent secondary damage. Please also pay attention to the application note and the related technical information.

Keep safety first in your circuit designs!

Mitsubishi Electric Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of non-flammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

- •These materials are intended as a reference to assist our customers in the selection of the Mitsubishi Electric Semiconductor product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Mitsubishi Electric Corporation or a third party.
- •Mitsubishi Electric Corporation assumes no responsibility for any damage, or infringement of any thirdparty's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
- •All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Mitsubishi Electric Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Mitsubishi Electric Corporation or an authorized Mitsubishi Electric Semiconductor product distributor for the latest product information before purchasing a product listed herein.

The information described here may contain technical inaccuracies or typographical errors. Mitsubishi Electric Corporation assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.

Please also pay attention to information published by Mitsubishi Electric Corporation by various means, including the Mitsubishi Electric Semiconductor home page (https://www.MitsubishiElectric.com/semiconductors/).

- •When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Mitsubishi Electric Corporation assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
- •Mitsubishi Electric Corporation semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Mitsubishi Electric Corporation or an authorized Mitsubishi Electric Semiconductor product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- •The prior written approval of Mitsubishi Electric Corporation is necessary to reprint or reproduce in whole or in part these materials.
- •If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.

Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.

•Please contact Mitsubishi Electric Corporation or an authorized Mitsubishi Electric Semiconductor product distributor for further details on these materials or the products contained therein.

Generally the listed company name and the brand name are the trademarks or registered trademarks of the respective companies.

© Mitsubishi Electric Corporation